

# EZ Exit LED Emergency System

*The innovative alternative to traditional emergency fixtures*



- Fits seamlessly into standard T-grid ceilings
- Replaces obtrusive “bug-eye” emergency lights
- Constant power emergency driver provides reliable lumen output
- Integrated test switch, multiple mounting options

*Fulham's new HotSpot EZ Exit Emergency System is changing the way people think about emergency lighting. High output linear LED strips install quickly in standard T-grid ceilings, with constant power emergency drivers mounted out of sight above the grid. During normal standby operation the EZ Exit system is almost invisible, but when the power goes out the LED strips automatically illuminate, providing at least 90 minutes of emergency lighting. EZ Exit kits are available in 24" and 48" module lengths, and include all the installation hardware required to turn a standard T-grid ceiling into a reliable LED emergency lighting solution.*



Normal conditions



Power outage- emergency LEDs activated

Specifications			
Input Voltage	100-277VAC, 50/60Hz	Output Type	Class 2
Recharge Time	24 Hours	Surge Protection	Per C62.41 (TVS)
Emergency Operation	90 Minutes	Protective Lens	1.2mm Frosted Polycarbonate V-0 Flame rated
Operating Temp. Range (Ta)	0°C to 50°C / 32°F to 122°F		
Module Case Temperature (Tc)	Tc max 90°C / 194°F	Lens Transmittance	15%
Estimated Lumen Maintenance	L70: >60,000Hrs / L90: 40,000Hrs	PCB Material	FR4
RFI/EMI	FCC PART15A Non-Consumer	Warranty	5 years from the manufacture date

Product Models							
Model number	Max Input Current (A)	Nominal Input Power (W)	Output Power (W)	Module Operating Voltage (VDC)	Max Lumen Output (lm)	Battery	Dimensions (L x W x H)
FHEZ10A24	0.087	5.7	10.7	26.2	1300	NiCd 9.6Vdc	23.9" x 1.44" x 1.86"
FHEZ10A24-CEC*							
FHEZ17A48	0.11	7.9	17	25.8	2200	NiCd 14.4Vdc	47.9" x 1.44" x 1.86"
FHEZ17A48-CEC*							

\* CEC Title 20 Compliant

**EZ Exit Kit includes:**



**FHEZ10A24, FHEZ10A24-CEC**

- 24" EZ Exit Luminaire,
- 10.7W HotSpot Constant Power Emergency Driver
- 2 Caddy clips, 2 Silver clips, 4 Screws
- 10' Extension harness



**FHEZ17A48, FHEZ17A48-CEC**

- 48" EZ Exit LED Luminaire,
- 17W HotSpot Constant Power Emergency Driver
- 2 Caddy clips, 2 Silver clips, 4 Screws
- 10' Extension harness

*Visit [Fulham.com](http://Fulham.com) for video of the EZ Exit in action and to download installation instructions*

**FULHAM** [www.fulham.com](http://www.fulham.com)

North America • China • Europe • India • Latin America

Fulham Headquarters: 12705 S. Van Ness Avenue, Hawthorne, CA 90250 Tel: +1 (323) 599-5000 Fax: +1 (323) 754-9060 • [order@fulham.com](mailto:order@fulham.com)

All trademarks are the property of their respective owners | ©Fulham Co. Inc., 2018 | PN: FLYER-HS-EZEXIT | REV: DEC18