


SPECIFICATION SHEET : SC-120-213-T5XL

This Is An Original Product From Fulham Co., Inc

Description : PONY Series, High Frequency Electronic, Rapid Start Ballast,

This Ballast Will Operate Following Lamps.



F8T5 / F13T5 / F14T5 / F21T5

ELECTRICAL DATA

INPUT VOLT: 120V ± 10%, 50/60Hz										
LAMP WATTS/TYPE	F13T5	F14T5	F8+F13T5	F21T5						
LAMPS OPERATED	2			1						
INPUT WATTS	32.55W	33.63W	25.72W	24.52W						
LINE CURRENT:	0.473A	0.493A	0.384A	0.373A						
POWER FACTOR	0.575	0.566	0.557	0.546						
BALLAST FACTOR	1.075	1.074	1.370	1.007						
EFFICACY FACTOR	3.302	3.193	5.325	4.109						
THD	122.6%	124.5%	134.3%	139.1%						
CURRENT CREST FACTOR	1.502	1.462	1.503	1.497						
EMI/RFI COMPLIANCE	FCC PART 18-A (NON-Cons um er)									
SOUND RATING	" A "									
BALLAST TYPE	RAPID START									
VOLTAGE TRANSIENTS	ANSI 62.41									
INPUT/PROTECTION	FUSE									
OUTPUT/PROTECTION	EOL									
MIN. OPERATING TEMP	-10°C (14°F)									
MAX. CASE TEMP	75 °C (167 ° F)									
APPROVALS/CLASS	UL /cUL LISTED, CLASS " P ", INDOOR									

